



Produktfamilj

AirSoft Multiple-Use Earplug

Advanced air pocket design, optimized for comfort



Product Numbers &



1030612

AirSoft - red polycord
SNR 30 H 29 - M 27 - L 25



1030610

AirSoft - uncorded
SNR 30 H 29 - M 27 - L 25



1030611

AirSoft - white nylon cord
SNR 30 H 29 - M 27 - L 25

Översikt

Viktigaste egenskaperna

- Advanced air pocket design features internal noise-blocking fins
- Four-flange profile creates better seal in the ear canal
- Less pressure in the ear canal eliminates that “plugged up” feeling
- Rounded flanges, tapered shape fits better in the ear canal
- Firm stem facilitates easy insertion and removal
- Outstanding noise-blocking protection

Rekommenderade branscher/rekommenderat användningsområde

- Jordbruk
- Kemi
- Byggindustri
- Livsmedel
- Skogsvård
- Myndigheter
- Polis
- Tillverkning
- Sjukvård
- Militären
- Gruvdrift
- Kommunala tjänster
- Olja och gas
- Läkemedel
- Stål och metaller
- Transport
- Vatten och energi
- Svetsning
- Kärnkraft

Risker

Föreskrifter

- 29 CFR 1910.95 - OSHA Occupational Noise Exposure (US)
- ANSI S3.19-1974 - Attenuation Test Protocol (US)
- Part II, (R.S.C. 1985, c. L-2) - Occupational Noise Standard (CAN)
- Z94.2-1994 - Attenuation Test Protocol (CAN)
- 2003/10/EC - EU Hearing Directive
- 89/686/EEC - European Directive/PPE
- Category II - EC Category PPE
- EN 352-2:1993 - EU Standards
- NOHSC: 1007 (2000) - National Standard for Occupational Noise (AUS/NZ)
- AS/NZS 1270:2002 - Attenuation Test Protocol (AUS/NZ)
- NR 15 - Security and Health of Work, Annexes 1 and 2, n°3.214/1978 - Occupational Noise Regulations (BR)
- ANSI S12.6/1997 - Method B - Attenuation Test Protocol (BR)

Tidigare varumärke

Howard Leight

Specifikationer

Color

- Blue

Shape

- 4 Flange

Material

- TPE

Packaging Options

- Polybag, Reusable Case

Cord Options

- Uncorded, Red Polycord, White Nylon Cord

NRR

- 27

Canada Class

- A

SNR

- 30

SLC80

- 26 dB / Class 5

EU Certifications

- European Directives – 89/686/EEC
- EC Category PPE – Category II
- Standards – EN 352-2:1993
- EC Certification Number – EC152
- EC Attestation Number – 152
- Laboratory – INSPEC

AUSNZ Standards

- Standardsmark License #1579

Trycksaker & dokument

Earplug Instruction Poster - EN

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/19799/1033.aspx

Instruction Manual - Airsoft (global)

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/4294986709/1033.aspx

Earplug Instruction Poster - ES

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/19802/1033.aspx

Earplug Instruction Poster - FR

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/19800/1033.aspx

Data Sheet Airsoft DPAS-30R, DPAS-30W, AS-1, AS-30R

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/Earplugs/15941/1033.aspx

EU Certificate - AirSoft

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Secured/Hearing_Protection/Earplugs/20031/1033.aspx

CE Certificate - AirSoft

Noise Thermometer Poster - AUS

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/24933/1033.aspx

Earplug Fitting Poster - AUS

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/24934/1033.aspx

Care & Maintenance of Earplugs and Earmuffs - AUS

http://www.honeywellsafety.com/Supplementary/Documents_and_Downloads/Hearing_Protection/24936/1033.aspx

Training & Proper Use

1. While holding the stem, reach a hand over your head and gently pull top of your ear up and back.
2. Insert the earplug so all flanges are well inside your ear canal.
3. If properly fitted, the tip of the earplug stem may be visible to someone looking at you from the front.
4. Proper Fit – If either or both earplugs do not seem to be fitted properly, remove the earplug and reinsert.
5. Removal – Gently twist earplug while slowly pulling in an outward motion for removal.
6. Acoustical Check – In a noisy environment, with earplugs inserted, cup your hands over your ears and release. Earplugs should block enough noise so that covering your ears with your hands should not result in a significant noise difference.

Ytterligare information

CARE + MAINTENANCE

- **INSPECT** - Prior to fitting, examine your earplugs for dirt, damage, deformation or extreme hardness. Discard immediately if compromised.

AirSoft Multiple-Use Earplug

- CLEAN - Wash Multiple-Use earplugs with mild soap and warm water only. Pat dry with a towel and store in a case when not in use. Do not treat with any other substances, as the earplug may degrade and compromise use.
- HYGIENE - With proper maintenance, Multiple-Use earplugs can last for 2-4 weeks.

RELATERADE PRODUKTER

© Honeywell International Inc.